

ICOM RESET

RADIO	RESET
2GAT	TURN RADIO ON,HOLD (LIGHT)&(FUN), TURN ON AND RELEASE
02AT	S/N <34,000 –PUSH BUTTON ON MAIN BOAD NEXT TO LITIUM BATT S/N >34,000 – HOLD(FUN) AND TURN RADIO ON
2SA	HOLD(LIGHT)&(MON) AND TURN RADIO ON
2SAT	HOLD (FUN) & (A) AND TURN RADIO ON
2SRA	HOLD (FUN) & (A) & (CLR)AND TURN RADIO ON
U2AT	HOLD (LIGHT) AND TURN RADIO ON
3SA	HOLD(LIGHT)&(MON) AND TURN RADIO ON
3SAT	HOLD (FUN) & (A) AND TURN RADIO ON
4GAT	TURN RADIO ON, HOLD (LIGHT) & (FUN), TURN RADIO OFF
4SA	HOLD(LIGHT)&(MON) AND TURN RADIO ON
4SAT	HOLD (FUN) & (A) AND TURN RADIO ON
4SRA	HOLD (FUN) & (A) & (CLR)AND TURN RADIO ON
U4AT	HOLD (LIGHT) AND TURN RADIO ON
12AT	HOLD (FUN) AND TURN RADIO ON
12GAT	TURN RADIO ON, HOLD (LIGHT) & (FUN), TURN RADIO OFF
24AT	HOLD (FUN) & (A) AND TURN RADIO ON
32AT	HOLD (FUN) & (A) & (LIGHT) AND TURN RADIO ON
228	HOLD (SQUELCH/MON) &(LOCK) AND TURN RADIO ON
229A	HOLD (SET) & (MW) AND TURN RADIO ON
271	REPROGRAM RAM CARD
275	HOLD (M-CL) AND TURN RADIO ON
375	HOLD (M-CL) AND TURN RADIO ON
448	HOLD (SQUELCH/MON) &(CLOCK) AND TURN RADIO ON
471	REPROGRAM RAM CARD
475	HOLD (M-CL) AND TURN RADIO ON
575	HOLD (M-CL) AND TURN RADIO ON
725	HOLD (FUN) & (MW) AND TURN RADIO ON
726	HOLD (FUN) & (MW) AND TURN RADIO ON
761	HOLD (M – CLEAR) AND TURN RADIO ON
765	HOLD (M – CLEAR) AND TURN RADIO ON
781	HOLD (M – CLEAR) AND TURN RADIO ON
900	HOLD (MR) AND TURN POWER OFF AND THEN ON AGAIN
901A	TURN RADIO ON, PUCH (CHECK) & (MW)
970	HOLD (MW) AND TURN RADIO ON
1201	HOLD (SQUELCH/MON) &(LOCK) AND TURN RADIO ON
1220	TURN RADIO OFF FOR A FEW MINUTES AND THEN PRESS SWITCH S1 ON LOGIC POWER ON
1271	REPROGRAM RAM CARD
1275	HOLD (M-CL) AND TURN RADIO ON
1520	TURN RADIO OFF FOR A FEW MINUTES AND THEN PRESS SWITCH S1 ON LOGIC POWER ON
1600	TURN RADIO OFF, WAIT A FEW MINUTES AND TURN POWER ON
2400	HOLD (SUB VOL) AND (MW) AND TURN POWER ON
2500	HOLD (SUB VOL) AND (MW) AND TURN POWER ON
3200	HOLD (FUN) AND TURN RADIO ON
3210	HOLD (SQUELCH/MON) &(LOCK) AND TURN RADIO ON